

Videotree

RS232 Codes

! This is a full list of codes for all models of TV's however not all TV's have all functions listed.

Number	Description	RS232 Code	Number	Description	RS232 Code
1	POWER ON	POWR01	30	CHANNEL6	NUMB06
2	POWER OFF	POWR00	31	CHANNEL7	NUMB07
3	VOLUME UP	RGHT00	32	CHANNEL8	NUMB08
4	VOLUME DOWN	LEFT00	33	CHANNEL9	NUMB09
5	CHANNEL UP	UPXX00	34	CHANNEL0	NUMB00
6	CHANNEL DOWN	DOWN00	35	-/--	NUMT00
7	MUTE ON	MUTE99	36	EXIT	EXIT00
8	MUTE OFF	MUTE99	37	ARC ON	ARCX01
9	HDMI1	IHDM01	38	ARCOFF	ARCX00
10	HDMI2	IHDM02	39	BLUE	BLUE00
11	HDMI3	IHDM03	40	RED	REDX00
12	USB1	IUSB01	41	YELLOW	YLOW00
13	RGB	IRGB01	42	GREEN	GREN00
14	SATELLITE DVBS	DVBS00	43	SOURCE	SRCE00
15	TERRESTRIAL DVBT	DVBT00	44	PAUSE/PLAY	PLPS00
16	COMPONENT	IYPB01	45	RECORD	RECX00
17	COMPOSITE	IAVX01	46	SLEEP	SLEP00
18	SCART	ISCT01	47	STOP	STOP00
19	SELECT	SLCT00	48	INFO	INFO00
20	EPG GUIDE	EPGX00	49	TEXT	TEXT00
21	LEFT	WEST00	50	Sub Title	SUBT00
22	RIGHT	EAST00	51	MENU	MENU00
23	UP	NRTH00	52	ENTER	ENTR00
24	DOWN	SUTH00	53	CEC ON	CECX01
25	CHANNEL 1	NUMB01	54	CEC OFF	CECX00
26	CHANNEL 2	NUMB02	55	CEC Status	CECX??
27	CHANNEL3	NUMB03	56	LIGHT 50%	LIGH50
28	CHANNEL4	NUMB04	57	LIGHT 75%	LIGH75
29	CHANNEL5	NUMB05	58	LIGHT 100%	LIGH00

After every command you will require a carriage return.

- Baud Rate is: 115200
- Parity bit: None
- Stop bit: 1 bit
- Flow Control: None
- Data Length: Data Length 8bits